

---

**GESCHAKELDE VOEDING SINGLE OUTPUT 200W 5.0V/40A**

**€ 57,95**

Excl. BTW: € 47,89

**Afbeeldingen**

---



**Beschrijving**

---

**Features**

- Enclosed case, screw terminals
- Universal input
- Overload protection, pulsing hiccup shutdown, auto recovery
- Protections: short circuit/over load/over voltage
- Built-in active PFC function
- Low profile



## Technical Specifications



|                             |   |
|-----------------------------|---|
| Input Voltage:              | 88...264V AC (47...63Hz)<br>124...370V DC |
| Input Inrush Current, Max.: | 40A                                       |
| Leakage Current, Max.:      | 1mA                                       |
| Output Voltage Adjustment:  | ±10%                                      |
| Over Load Protection:       | 105...135%                                |
| Withstand Voltage           |   |
| I/P-O/P:                    | 3000V AC                                  |
| I/P-FG:                     | 2000V AC                                  |
| O/P-FG:                     | 500V AC                                   |
| Operating Temperature:      | -30...+70°C                               |
| Weight:                     | 720g                                      |

I/P = Input, O/P = Output, FG = Frame Ground



| Part Nr.     | $U_A$ | $I_A$    | $P_A$  | $DU_A$ | $U_{RN}$             | h    |
|--------------|-------|----------|--------|--------|----------------------|------|
|              | [V]   | [A]      | [W]    | [%]    | [mV <sub>p-p</sub> ] | [%]  |
| RSP-200-2.5  | 2,5   | 0...40   | 100    | 2      | 100                  | 79,5 |
| RSP-200-3.3  | 3,3   | 0...40   | 132    | 2      | 100                  | 81,5 |
| RSP-200-4    | 4     | 0...40   | 160    | 2      | 100                  | 84   |
| RSP-200-5    | 5     | 0...40   | 200    | 2      | 150                  | 85,5 |
| RSP-200-7.5  | 7,5   | 0...26,7 | 200,25 | 2      | 150                  | 89   |
| RSP-200-12   | 12    | 0...16,7 | 200,4  | 1      | 150                  | 89   |
| RSP-200-13.5 | 13,5  | 0...14,9 | 201,15 | 1      | 150                  | 89   |

|            |    |          |        |   |     |      |
|------------|----|----------|--------|---|-----|------|
| RSP-200-15 | 15 | 0...13,4 | 201    | 1 | 150 | 89,5 |
| RSP-200-24 | 24 | 0...8,4  | 201,6  | 1 | 150 | 89,5 |
| RSP-200-27 | 27 | 0...7,5  | 202,5  | 1 | 200 | 89   |
| RSP-200-36 | 36 | 0...5,56 | 200,16 | 1 | 220 | 90   |
| RSP-200-48 | 48 | 0...4,2  | 201,6  | 1 | 240 | 90   |

$U_A$  = Output Voltage,  $I_A$  = Output Current Range,  $P_A$  = Output Power,  $U_{adj}$  = Output Voltage Adjustment,  $DU_A$  = Output Voltage Tolerance,  $U_{RN}$  = Ripple & Noise,  $h$  = Efficiency

## Productinformatie

|               |          |
|---------------|----------|
| Artikelnummer | RSP20005 |
| Merk          | MEANWELL |
| Is on Sale    | Nee      |

