

ALBRECHT AE 6110 VOX

€ 74,95

Excl. BTW: € 61,94

Afbeeldingen



Beschrijving

Nu met standaard gelijkstroomsnoer en een extra gelijkstroomsnoer met sigarettenaanstekerstekker.

De Albrecht AE 6110 VOX CB-radio is zo ongelooflijk klein dat hij vrijwel overal past, hij is iets meer dan 100 mm breed en diep en slechts 25 mm dik.

Ondanks zijn kleine formaat beschikt hij over alle functies die u van een moderne CB-radio op instapniveau mag verwachten, waaronder AM/FM-meerkanaalsbediening, automatische squelch, 6-segment LCD S-meter, RF-versterking en scanfuncties. De AE 6110 VOX wordt tevens geleverd met een vaste op- en neerwaartse microfoon. Albrecht AE-6110, de kleine CB die grote indruk maakt.

Frequentiebereik: 26,965 - 27,405 MHz

Features

- Modulation: AM / FM
- Multi-bands: Yes
- Output power: 4 Watt
- Channels: 40 AM / FM
- Display type: LCD display
- Display colors: Orange
- VOX Function: Yes
- Squelch: ASQ (Automatig Squelch Systeem) / Manual squelch /
- Emergency channel: Yes
- Keypad lock: Yes
- Scan function: Yes
- External speaker socket: Yes
- S-meter: Yes
- RF gain: Yes

Electrical data

- Voltage: 13,8 Volt
- Operating temperature: -20° to +55° C
- Frequency control: PLL synthesizer

Transmitter

- Frequency allowance: ± 300 Hz
- Modulation AM: from 85% to 90%
- Modulation FM: 1.9 kHz
- Drain: 13.2 Volt: 2.0 A

Receiver

- AM sensitivity: 1.0 μ V for 10 dB SINAD
- FM sensitivity: 1.0 μ V for 20 dB SINAD
- Frequency response: 300 Hz - 3 kHz
- Adjacent channel selectivity: 60 dB
- Maximum audio power: 1 Watt
- Internal speaker: 8 Ohm, round
- Image rejection: 70 dB

Mechanical data

- Length: 100 mm
- Height: 25 mm

- Width: 102 mm
- Weight: 450 gram
- Antenna connector: UHF (PL) female (SO-239)
- Mike connector: RJ45 connector

Inside the box

- Transceiver: 1 pcs
- Microphone: 1 pcs
- Mounting bracket: 1 pcs
- Power lead: 2 pcs
- User Manual: English, German, Spanish, Italian, French, Polish, Romania

Productinformatie

Artikelnummer	AE611OVOX
Merk	ALBRECHT
Is on Sale	Nee

