

STABO XM 5008E-R VOX

€ 359,95

Excl. BTW: € 297,48

Afbeeldingen



Beschrijving

De Stabo XM 5008E-R VOX is een mobiel CB-radioapparaat en kan worden gebruikt op 12 en 24 Volt. De XM 5008E-R beschikt over een instelbare VOX-functie (5 niveaus) die het mogelijk maakt om handsfree te communiceren met de

optionele Stabo VOX-microfoon. Bij deze versie wordt een originele DIN-houder van Stabo meegeleverd.

Frequentiebereik: 26,965 - 27,405 MHz

## Features

- Modulation: AM / FM
- Multi-bands: Yes
- Output power: 4 Watt
- Channels: 40 AM / FM
- Front speaker: Yes
- Display type: LCD display
- Display colors: Orange
- VOX Function: Yes
- Noise blanker: Yes
- Squelch: ASQ (Automatig Squelch Systeem) / Manual squelch /
- Emergency channel: Yes
- Scan function: Yes
- Memory channels: Yes
- External speaker socket: Yes
- S-meter: Yes
- TOT (time out timer): Yes
- Din mount: Yes
- Roger Beep: Yes

## Electrical data

- Voltage: 13,8 Volt / 24 Volt /
- Operating temperature: -10° to +55° C

## Transmitter

- Audio frequency response: 300 Hz - 3 kHz
- Microphone sensitivity: <5 mV
- Frequency allowance: ± 300 Hz
- Drain: 13.2 Volt: 2 A max / 24 Volt: 2 A max

## Receiver

- AM sensitivity: 0.7  $\mu$ V - 110 dBm
- FM sensitivity: 0.4  $\mu$ V - 115 dBm
- Frequency response: 300 Hz - 3 kHz
- Adjacent channel selectivity: 60 dB
- Squelch sensitivity: min. 0.2  $\mu$ V - 120 dBm min. / 10 mV -27 dBm max.
- IF rejection: 65 dB
- Intermodulation suppression: 50 dB
- Drain: 250 mA nominal / 750 mA max.

## Mechanical data

- Length: 180 mm
- Height: 60
- Width: 170 mm

- Weight: 1000 gram
- Antenna connector: UHF (PL) female (SO-239)
- Mike connector: 6 pin connector

## Inside the box

- Transceiver: 1 pcs
- Microphone: 1 pcs
- Fixing screws: 1 set
- Power lead: 1 pcs
- DIN mount: 1 pcs
- User manual: English, German, French, Polish,

### Productinformatie

---

Artikelnummer	XM5008ER
Merk	STABO
Is on Sale	Nee

