

GESCHAKELDE VOEDING SINGLE OUTPUT 636W 12V/53A

€ 169,00

Excl. BTW: € 139,67

Afbeeldingen



Beschrijving

Note

No load power consumption when Remote Control is off.
You will find installation material in product group L9985.
These power supplies are considered as a component that has to be installed in a final equipment.



HRP-600



Features

- Enclosed case, built-in fan, screw terminals
- Universal input
- Withstands 300V AC surge input for 5s
- Overload protection, current limiting, auto recovery
- Protections: short circuit/over load/over voltage
- Built-in active PFC function
- Long life 105°C electrolytic capacitors
- Built-in remote sense function
- DC OK signal



HRPG-600



Features

Same as HRP-600 but additional:

- Built-in remote On/Off control
- Low no load power consumption <0,75W
- Built-in auxiliary power, Stand by 5V/0,3A



Technical Specifications



Input Voltage:	85...264V AC (47...63Hz)
	120...370V DC
Input Inrush Current, Max.:	70A
Leakage Current, Max.:	1,2mA
Over Load Protection:	105...135%
Withstand Voltage	
I/P-O/P:	3000V AC
I/P-FG:	2000V AC
O/P-FG:	500V AC

Operating Temperature:	-40...+70°C
Weight:	1580g

I/P = Input, O/P = Output, FG = Frame Ground



Part Nr.	U_A	I_A	P_A	U_{adj}	DU_A	U_{RN}	h
	[V]	[A]	[W]	[V]	[%]	[mV _{p-p}]	[%]
HRP-600-3.3	3,3	0...120	396	2,8...3,8	2	100	78,5
HRP-600-5	5	0...120	600	4,3...5,8	2	100	82
HRP-600-7.5	7,5	0...80	600	6,8...9	2	100	86
HRP-600-12	12	0...53	636	10,2...13,8	1	120	88
HRP-600-15	15	0...43	645	13,5...18	1	150	88
HRP-600-24	24	0...27	648	21,6...28,8	1	150	88
HRP-600-36	36	0...17,5	630	28,8...39,6	1	200	89
HRP-600-48	48	0...13	624	40,8...55,2	1	240	89
HRPG-600-3.3	3,3	0...120	396	2,8...3,8	2	100	78,5
HRPG-600-5	5	0...120	600	4,3...5,8	2	100	82
HRPG-600-7.5	7,5	0...80	600	6,8...9	2	100	86
HRPG-600-12	12	0...53	636	10,2...13,8	1	120	88
HRPG-600-15	15	0...43	645	13,5...18	1	150	88
HRPG-600-24	24	0...27	648	21,6...28,8	1	150	88
HRPG-600-36	36	0...17,5	630	28,8...39,6	1	200	89
HRPG-600-48	48	0...13	624	40,8...55,2	1	240	89

U_A = Output Voltage, I_A = Output Current Range, P_A = Output Power, U_{adj} = Output Voltage Adjustment, DU_A = Output Voltage Tolerance, U_{RN} = Ripple & Noise, h = Efficiency



Labelling





Productinformatie

Artikelnummer	HRP60012
Merk	MEANWELL

