

DC-DC CONVERTER 18-36V:5V 3A IN BEHUIZING

€ 20,95

Excl. BTW: € 17,31

Afbeeldingen



Beschrijving

15W Single Output DC-DC Converter

2:1 wide input range

Protections: Short circuit/Over load /voltage

Built-in EMI filter, low ripple noise

100% full load burn-in test

Low cost

High reliability

OUTPUT

DC VOLTAGE: 5V

RATED CURRENT: 3,0A

CURRENT RANGE: 0 ~ 3.0A

RATED POWER: 15W

RIPPLE & NOISE (max.) Note.2: 100mVp-p

VOLTAGE ADJ. RANGE: 4.75 ~ 5.5VDC

VOLTAGE TOLERANCE Note.3: +/- 2.0%

LINE REGULATION: +/- 0.5%

LOAD REGULATION: +/- 0.5%

SETUP, RISE, HOLD UP TIME: 2.5s, 50ms, ---12VDC/24VDC/48VDC at full load

INPUT

VOLTAGE RANGE: 18 ~ 36VDC
INPUT EFFICIENCY (Typ.): 76%
DC CURRENT: 0.9A/24VDC

DIMENSION: 78x51x28mm (LxWxH)

Productinformatie

Artikelnummer	SD15B5
Merk	MEANWELL
Is on Sale	Nee

