

**PRESIDENT WALKER II ASC AM/FM**

**€ 224,91**

Excl. BTW: € 185,88

**Afbeeldingen**





## Beschrijving

---

De President Walker II ASC. Is als de originele Walker maar met een analoge signaalsterktemeter en draibare kanaalwissel. Het is echter een compleet andere radio, met een LCD-display met meerdere functies, inclusief kanaal- en frequentie-uitlezing. Nieuwe functies zijn: digitale SWR-meter, 7-kleurendisplay, variabel vermogen, USB-laadaansluiting, roger bleep, talk back & selectie van elektrische/dynamische microfoon.

Frequentiebereik: 26,965 - 27,405 MHz

## Features

- Modulation: AM / FM
- Multi-bands: Yes
- Output power: 4 Watt
- Channels: 40 AM / FM
- Display type: LCD display
- Display colors: Green / Orange / Purple / Blue / Cyaan / Yellow / Clear Blue
- VOX Function: Yes
- USB: Yes
- Noise blanker: Yes
- Squelch: ASQ (Automatig Squelch Systeem) / Manual squelch /
- Emergency channel: Yes
- Scan function: Yes
- Memory channels: Yes
- External speaker socket: Yes
- External PA socket: Yes
- S-meter: Yes
- MIC gain: Yes
- RF gain: Yes
- TOT (time out timer): Yes
- Dual watch: Yes
- Roger Beep: Yes
- External VOX socket: Yes

# Electrical data

- Voltage: 13,8 Volt

# Transmitter

- Audio frequency response: 300 Hz - 3 kHz
- Microphone sensitivity: 3.0 mV
- Frequency allowance:  $\pm$  200 Hz
- Transmission interference: inferior to 4 nW (- 54 dBm)
- Emitted power in the adjacent channel: inferior a 20  $\mu$ W
- Modulated signal distortion: 1.8 %
- Drain: 13.2 Volt: <2.0 A

# Receiver

- AM sensitivity: 0,5  $\mu$ V - 113 dBm
- FM sensitivity: 0,35  $\mu$ V - 116 dBm
- Frequency response: 300 Hz - 3 kHz
- Adjacent channel selectivity: 60 dB
- Maximum audio power: 3 Watt
- Squelch sensitivity: min. 0.2  $\mu$ V - 120 dBm / max. 1 mV - 47 dBm
- Frequency image rejection rate: 60 dB
- Intermediate image rejection rate: 70 dB
- Drain: 13.2 Volt: 180 - 500 mA

# Mechanical data

- Length: 160 mm
- Height: 52 mm
- Width: 170 mm
- Weight: 1100 gram
- Antenna connector: UHF (PL) female (SO-239)
- Mike connector: 6 pin connector

# Inside the box

- Transceiver: 1 pcs
- Microphone: 1 pcs
- Fixing screws: 1 set
- Mounting bracket: 1 pcs
- Power lead: 1 pcs
- User Manual: English, Spanish, French, Polish

## Productinformatie

---

|               |           |
|---------------|-----------|
| Artikelnummer | WALKERII  |
| Merk          | PRESIDENT |
| Is on Sale    | Nee       |

