

MOBIELE CB ZENDER 27MHZ 40KAN 4W

€ 74,95

Excl. BTW: € 61,94

Afbeeldingen



Beschrijving

De K-PO Midland 98 Plus is een compacte radio die echt boven zijn gewicht uitstijgt. Ondanks dat het een van de meest betaalbare radio's is, bevat het hoge normen op het gebied van bouwkwiteit en technologie, waardoor het een zeer aantrekkelijke kleine CB is.

Frequentiebereik: 26,965 - 27,405 MHz

Features

- Modulation: FM
- Output power: 4 Watt
- Channels: 40 FM
- Display type: Backlight

- Display colors: Orange
- Squelch: Manual squelch
- Emergency channel: Yes
- External speaker socket: Yes
- External S-meter socket: Yes
- S-meter: Yes

Electrical data

- Voltage: 13,8 Volt
- Frequency control: Precision PLL synthesizer

Transmitter

- Audio frequency response: 300 Hz - 3 kHz
- Modulation FM: 1.8 kHz to ± 0.2 kHz

Receiver

- Frequency response: 300 Hz - 3.0 kHz
- Adjacent channel selectivity: 65 dB
- Sensitivity with ESP: 0.3 μ V for 20 dB SINAD
- Sensitivity without ESP: 0.7 μ V for 20 dB SINAD
- Receiving system: Dual conversion superheterodyne
- IF frequencies: Double conversion 1st 10.695 MHz / 2nd 455 kHz
- Audio distortion: Less than 8% @ 1 kHz

Mechanical data

- Length: 120 mm
- Height: 40 mm
- Width: 190 mm
- Weight: 737 gram
- Antenna connector: UHF (PL) female (SO-239)
- Mike connector: 6 pin connector

Inside the box

- Transceiver: 1 pcs
- Microphone: 1 pcs
- Fixing screws: 1 set
- Mounting bracket: 1 pcs
- User Manual: English

Productinformatie

Artikelnummer	KPO98E
Merk	K-PO
Is on Sale	Nee

