

K-PO AV-CN600 SWR METER

€ 124,94

Excl. BTW: € 103,26

Afbeeldingen



Beschrijving

De K-PO AV-CN600 is een kruisnaaldmeter en meet tegelijkertijd het voorwaartse vermogen, het gereflecteerde vermogen en de SWR.

Electrical data

- Backlight display / meter: Yes
- Impedance: 50 Ohm
- Power range: 1.8 - 160 MHz: 30 / 300 / 3000 Watts / 140 - 525 MHz: 30 / 300 / 600 Watts
- Accuracy: 30 Watts: $\pm 5\%$ / 300 Watts: $\pm 5\%$ / 600 Watts: $\pm 7.5\%$ / 3000 Watts: $\pm 7.5\%$
- Minimum Power for SWR: 0.5 Watt
- Insertion loss: 0.2 dB
- Testing function: SWR and Power (FWD and REF / AVG and PEP)
- Voltage: 13.8 Volt, for display lightning only
- Continuous power rating 1.8 - 160 / 140 - 525 MHz: 300 Watts CW / SSB
- Maximum power handling 1.8 - 160 MHz: 3 kW 15 sec / 2 kW 30 sec / 1 kW 60 sec

- Maximum power handling 140 - 525 MHz: 600 Watts CW / SSB 25 sec on, 35 sec off
- Output connector: 2x UHF (PL) female
- Length: 150 mm
- Height: 65 mm
- Width: 100 mm
- Weight: 720 gram

Inside the box

- Meter: Yes
- DC power cable: Yes
- Installation manual: English

Productinformatie

| | |
|---------------|---------|
| Artikelnummer | AVCN600 |
| Merk | K-PO |
| Is on Sale | Nee |

