

K-PO AV-CN400 SWR METER

€ 99,95

Excl. BTW: € 82,60

Afbeeldingen



Beschrijving

De K-PO AV-CN400 is een kruisnaaldmeter en meet tegelijkertijd het voorwaartse vermogen, het gereflecteerde vermogen en de SWR. AVG/PEP-schakelaar om gemiddeld vermogen of SSB/PEP te selecteren. Frequentiebereik van 140 - 525 MHz.

De meter is zeer gebruiksvriendelijk waardoor hij bruikbaar is voor het testen van zowel basis- als mobiele installaties en voor permanente installatie in uw opstelling.

Electrical data

- Backlight display / meter: Yes
- Impedance: 50 Ohm
- Power range: 30 / 300 / 600 Watts
- Accuracy: 30 Watts: $\pm 5\%$ / 300 Watts: $\pm 5\%$ / 600 Watts: $\pm 7.5\%$
- Minimum Power for SWR: 0.5 Watt
- Insertion loss: 0.2 dB

- Testing function: SWR and Power (FWD and REF / AVG and PEP)
- Voltage: 13.8 Volt, for display lightning only
- Continuous power rating: 300 Watts CW/SSB
- Maximum power handling: 600 Watts CW/SSB 25 sec on, 35 sec off

- Input connector: UHF (PL) female
- Output connector: UHF (PL) female
- Length: 150 mm
- Height: 65 mm
- Width: 100 mm
- Weight: 630 gram

Inside the box

- Meter: Yes
- DC power cable: Yes
- Installation manual: English

Productinformatie

Artikelnummer	AVCN400
Merk	K-PO
Is on Sale	Nee

