
CX500 MIDI-TOWER ZWART RGB ZONDER VOEDING

€ 79,94

Excl. BTW: € 66,07

Afbeeldingen



Beschrijving

The DAP CX Series power amplifiers are the solution when true quality is needed in an affordable price range. The CX Series are 5 models representing output powers from stereo 200W until 1450W. All including the best protection circuits and built in a strong solid housing to achieve many years of reliable power. They are the best mobile choice for musicians, DJs, and entertainers but due to the 256mm depth (excl. CX-3000) also perfect for installations in discos, pubs or any kind of public areas.

Specifications

Output Power Stereo: 8 Ohm: 2x 150 Watt RMS
4 Ohm: 2x 200 Watt RMS
2 Ohm: Not Allowed

Output Power Bridge: 8 Ohm: 400 Watt RMS
4 Ohm: Not Allowed

Frequency Response: 20 - 20,000 Hz, +0-1 dB

THD: < 0.5%

Damping Factor at 8 Ohm: > 200

Crosstalk 1Khz: -75dB

Crosstalk 20kHz: -58dB

Signal to Noise Ratio: > 100dB A-weighted

Input Sensitivity: 0,775V / 1,4V

Input Impedance: 20 kOhm Balanced

10 kOhm Unbalanced

Protection: Clip Limiter (Fixed)

Short Circuit

Overheat

Overload

DC Voltage

Soft Start

Output Modes: Stereo / Parallel / Bridge

Cooling: Speed regulated fan

Airflow: Front to Back

Input / Link Connectors: XLR

Output Connectors: 2x Speakon

Dimensions (LxWxH): 482 x 256 x 88 mm

Net Weight: 10 kg

Power Supply: 230V / 50 Hz

Productinformatie

Artikelnummer	CX500
Merk	ANTEC

