

VOORVERSTERKERBUIS 9P NOVAL DUBBEL TRIODE

€ 42,50

Excl. BTW: € 35,12

Afbeeldingen



Beschrijving

R. F. DOUBLE TRIODE

Base: NOVAL

Uf = 6,3 V

If = 365 mA

Typical

characteristic:

Ua = 90 V

$U_g = -1,3 \text{ V}$
 $I_a = 15 \text{ mA}$
 $S = 12,5 \text{ mA/V}$
 $R_i = 2,6 \text{ k}\Omega$
 $i = 33$
 Limiting values:
 $U_{a0} = 550 \text{ V}$
 $U_a(I_a=0) = 400 \text{ V}$
 $U_a = 220 \text{ V}$
 $U_a(P_{ar} < 0,8 \text{ W}) = 250 \text{ V}$
 $P_{aR} = 1,5 \text{ W}$
 $W_{g1R} = 0,03 \text{ W}$
 $I_k = 20 \text{ mA}$
 $U_g = -100 \text{ V}$
 $R_g = 1 \text{ M}\Omega$
 $U_{+k/f-} = 120 \text{ V}$
 $U_{-k/f+} = 60 \text{ V}$
 $R_{k/f} = 20 \text{ k}\Omega$
 Capacitances:
 system I. system II.
 $c_{g/k} = 3,1 \text{ pF}$
 $c_a = 0,18 \text{ pF}$
 $c_{g/a} = 1,4 \text{ pF}$

Productinformatie

| | |
|---------------|---------------|
| Artikelnummer | E88CC |
| Merk | JJ ELECTRONIC |
| Is on Sale | Nee |

