

## BASIS CB ANTENNE BOOMERANG 27-W

€ 64,95

Excl. BTW: € 53,68

### Afbeeldingen



### Beschrijving

#### Features:

- CB & 10m Balcon or temporary installation antenna
- Mono-band
- Omnidirectional
- Factory tuned at mid-band
- Tunable by whip length adjusting
- BOOMERANG 27 W: tapered glass fibre whip and radial with inside helical winding

#### Electrical Data

- Type:  $1/4 \lambda$  boomerang
- Frequency range: 27-28.5 MHz
- Impedance:  $50\Omega$  unbalanced
- Radiation (H-plane):  $360^\circ$  omnidirectional

- Polarization: vertical
- Gain: 0 dBd, 2.15 dBi
- Bandwidth at S.W.R. 2:1:  
BOOMERANG 27 W: 700 KHz
- S.W.R. at res. freq.:  $\leq 1.2:1$

- Max. power:  
BOOMERANG 27 W: 150 Watts (CW) continuous, 450 Watts (CW) short time
- Feed system / Position: Direct / center
- Connector: UHF-female

#### Mechanical Data

- Materials: Aluminium, Steel, Nylon, Glass fibre, Copper
- Wind load:  
BOOMERANG 27 W: 23 N at 150 Km/h
- Wind resistance: 140 Km/h
- Wind surface:  
BOOMERANG 27 W: 0.02 m<sup>2</sup>
- Height (approx.):  
BOOMERANG 27 W: 2870 mm
- Weight (approx.):  
BOOMERANG 27 W: 800 gr
- Radial length (approx.): 1130 mm

### Productinformatie

Artikelnummer	11087
Merk	SIRIO
Is on Sale	Nee

