


OMVORMER 24VDC-230VAC 1700W GEMODIFICEERDE SINUSGOLF

€ 439,00

Excl. BTW: € 362,81

Afbeeldingen



Beschrijving

Features

- Modified sine wave output
- Power On/Off switch
- Front panel indicator for operation status
- Battery low alarm, Battery low shutdown
- Protections: over voltage/over temperature/overload/output short/input reverse polarity
- Built-in fan On/Off control function



Technical Specifications



| | |
|-------------------|-----------|
| Input Voltage: | See Table |
| Output Voltage: | 230V AC |
| Output Frequency: | 50Hz ±1% |

| | |
|-----------------------|--------------------|
| Output Rated Power: | 1500W |
| Output Surge Power: | 3000W |
| Wave Form: | Modified Sine Wave |
| Overvoltage | |
| A301-1K7-F3: | 15...16V |
| A302-1K7-F3: | 29...31V |
| Operating Temperature | |
| 100% Load: | 0...+30°C |
| 70% Load: | 0...+40°C |
| Weight: | 5500g |



| Part Nr. | U_E | I_E | U_{BA} | U_{BL} | h |
|-------------|---------|-------|----------------|-----------------|-----|
| | [V] | [A] | [V] | [V] | [%] |
| A301-1K7-F3 | 10...15 | 170 | $10^{\pm 0,5}$ | $9,5^{\pm 0,5}$ | 82 |
| A302-1K7-F3 | 21...30 | 85 | $21^{\pm 0,8}$ | $20^{\pm 0,8}$ | 85 |

U_E = Input Voltage Range, I_A = Input Current, U_{BA} = Battery Low Alarm, U_{BL} = Battery Shutdown, h = Efficiency

Productinformatie

| | |
|---------------|----------|
| Artikelnummer | A302-1K7 |
| Merk | MEANWELL |

