

DC-DC CONVERTER 9,2-18V:12V 1.25A IN BEHUIZING

€ 20,95

Excl. BTW: € 17,31

Afbeeldingen



Beschrijving

15W Single Output DC-DC Converter
2:1 wide input range
Protections: Short circuit/Over load /voltage
Built-in EMI filter, low ripple noise
100% full load burn-in test
Low cost
High reliability

OUTPUT

DC VOLTAGE: 12V
RATED CURRENT: 1,25A
CURRENT RANGE: 0 ~ 1.25A
RATED POWER: 15W
RIPPLE & NOISE (max.) Note.2: 120mVp-p
VOLTAGE ADJ. RANGE: 10.8 ~ 13.2VDC
VOLTAGE TOLERANCE Note.3: +/- 1.0%
LINE REGULATION: +/- 0.3%
LOAD REGULATION: +/- 0.3%
SETUP, RISE, HOLD UP TIME: 2.5s, 50ms, --12VDC/24VDC/48VDC at full load

INPUT

VOLTAGE RANGE: 9,2 ~ 18VDC
INPUT EFFICIENCY (Typ.): 72%
DC CURRENT: 1.9A/12V

DIMENSION: 78x51x28mm (LxWxH)

Productinformatie

Artikelnummer	SD15A12
Merk	MEANWELL
Is on Sale	Nee

